

Parameter settings as well as history and maintenance information are permanently saved in the Eeprom. Faulty data has been discovered after restart or later on during continuous testing:



### Reasons for Eeprom defective

- An old software version has been installed (downgrade) which could not find compatible data in the Eeprom.
- Numerous power failures or by-pass of the mains supply.

### How to rectify

The error can only be eliminated by downloading the factory settings. As a consequence, all the current settings get lost and the door controller must be configured again. If this does not rectify the issue a new control panel will be required.

### DFA-127

- 8 Flash operator
- Wait 10 seconds
- 9 Flash operator
- Remove plug 14-15 and refit within 10 seconds
- When language shows on the BDE-D carry out another 8 flash
- Wait 10 seconds and fully reconfigure

### STA-20/FTA-20

- 8 Flash operator
- Wait 10 seconds
- 9 Flash operator
- Remove plug 1-12 and refit within 10 seconds
- When language shows on the BDE-D carry out another 8 flash
- Wait 10 seconds and fully reconfigure

